

- 1 EXISTING TO REMAIN ELECTRICAL / DATA / FIRE ALARM / FIRE PROTECTION DEVICE UNLESS NOTED OTHERWISE. REWORK WITH NEW WALL / CEILING / FLOOR AS NEEDED. RECIRCUIT AS SHOWN IF INDICATED.
- 2 EC TO FURNISH AND INSTALL NEW ELECTRICAL / LIGHT / POWER / DATA / FIRE ALARM / FIRE PROTECTION DEVICE(S) AS SHOWN. EC TO REUSE EXISTING LOCAL CIRCUIT(S) IF NO CIRCUIT INDICATED. EC TO VERIFY NEW LOADS DO NOT OVERLOAD CIRCUIT.
- 3 EC TO RELOCATE EXISTING ELECTRICAL / LIGHT / POWER / DATA / FIRE ALARM / FIRE PROTECTION DEVICE(S) TO LOCATION SHOWN.
- 4 EC TO FURNISH AND INSTALL NEW OCCUPANCY CONTROLLED RECEPTACLE TO BE CONTROLLED BY 2ND POWER PACK OF OCCUPANCY SENSOR. REFER TO LIGHTING PLANS. RECEPTACLE TO BE LEVITON 5362-SIW (2 EACH FOR QUAD RECEPTACLE). OCCUPANCY CONTROLLED HALF OF RECEPTACLE TO BE CONTROLLED BY 2ND LIGHTING POWER PACK. CONSTANT POWER TO GO TO REMAINING HALF OF RECEPTACLE. EC TO BREAK TANG BETWEEN RECEPTACLE HALVES.
- 5 GENERAL NOTE TYPICAL OF PROJECT: "DAISY CHAINING" OF GFI RECEPTABLES IS PROHIBITED. EACH RECEPTACLE TO BE GFI. TYPICAL OF GFI RECEPTABLES.
- 6 GENERAL NOTE TYPICAL OF PROJECT: DATA CONDUIT TO BE INDIVIDUAL 3/4" (MINIMUM) CONDUIT FROM DATA JACK TO ABOVE CEILING. COMBINING OF CONDUITS IS PROHIBITED UNLESS NOTED OTHERWISE. INCLUDE ONLY ONE DATA JACK / TERMINATION UNLESS NOTED OTHERWISE. TYPICAL OF DATA OUTLETS.
- 7 EC TO FURNISH AND INSTALL NEW GFI RECEPTABLES TO REPLACE EXISTING NON-GFI RECEPTABLES.
- 8 EC TO INCLUDE TEMPORARY POWER POLE AND DATA POLE TO RECEPTIONIST TEMPORARY LOCATION DURING PHASE I CONSTRUCTION. VERIFY EXACT LOCATION IN FIELD. REMOVE POWER AT COMPLETION OF PHASE I CONSTRUCTION. DATA TO BE REPURPOSED FOR PERMANENT LOCATION.



Copyright © 2017 Root Engineering.			
Drawing Title			
ELECTRICAL POWER PLANS			
Drawing No.			
E2			
Scale			
Dwg By	XX	Check By	XX
		Consult. JOB NO.	XXXXXX